

# V-Synth GT

# Q&A



## A collection of popular articles from the V-Synth GT knowledge base

How Do I Format a USB Flash Drive? .....	2
How Do I Assign My Sample to a Patch? .....	3
How Do I Save a Patch or Tone? .....	4
How Do I Load a V-Synth or V-Synth XT Project Into the V-Synth GT? .....	5
How Do I Perform a Factory Reset? .....	6
How Do I Find V-Synth GT Articles in the RolandUS.com Knowledge Base? .....	7



## V-Synth GT

### How Do I Format a USB Flash Drive?

---

**Warning!** Formatting a USB flash drive completely erases its contents. Proceed with caution!

- 1 Press the **UTILITY MODE** button.
- 2 Touch **Format**.
- 3 Touch **USB Memory**.
- 4 Touch **OK**.
- 5 When the V-Synth GT asks if you're sure you want to proceed, touch **OK**.

# Roland® V-Synth GT

## How Do I Assign My Sample to a Patch?

---

- 1 In the upper left-hand corner of the screen, touch the Menu icon.
- 2 Touch **Patch Init**.
- 3 When the V-Synth GT asks if you're sure you want to proceed, touch **OK**.
- 4 Press the PRO EDIT button.
- 5 At the bottom of the screen, touch **OSC 1**.
- 6 To the left of the screen, touch **OSC Type**.
- 7 Touch **PCM OSC**.
- 8 In the Waveform section, touch the little magnifying glass—the OSC 1 Wave List appears.
- 9 Navigate to the sample you saved, and select it.
- 10 Touch **OK**.

## V-Synth GT

### How Do I Save A Patch Or Tone?

---

To write a patch:

- 1 In the upper right-hand corner of the screen, touch the Menu icon.
- 2 In the pulldown menu, touch **Patch Write**.
- 3 Turn the VALUE dial to select the destination to which you want to write the patch, and then touch **OK**.

To write a tone:

- 1 In the upper right-hand corner of the screen, touch the Menu icon.
- 2 In the pulldown menu, touch **Tone Write**.
- 3 Turn the VALUE dial to select the destination to which you want to write the tone, and touch **OK**.

## V-Synth GT

### HOW DO I LOAD A V-SYNTH OR V-SYNTH XT PROJECT INTO THE V-SYNTH GT?

---

Projects from both the original V-Synth 2.0 and higher and the V-Synth XT rack can be loaded into the V-Synth GT:

- 1 Connect a USB flash drive to your computer.
- 2 On your computer, create a folder named “XT” on the USB drive.
- 3 Copy the V-Synth 2.0 or V-Synth XT project to the XT folder on the USB drive.
- 4 Once the copy’s complete, eject the USB drive from your computer.
- 5 Connect the USB drive to the V-Synth GT.
- 6 Press the UTILITY button.
- 7 Touch **Project**.
- 8 Touch **Convert Project**.
- 9 Select the desired project and touch **OK**.
- 10 When the V-Synth GT asks if you’re sure you want to proceed, touch **OK**.

**Note:** Converting a project may take several minutes.

## HOW DO I PERFORM A FACTORY RESET?

---

**Warning!** A factory reset returns the V-Synth GT to its factory state, clearing all of your work. Back up anything you want to preserve before porceeding.

- 1 Press the UTILITY MODE button.
- 2 Touch **Factory Reset**.
- 3 Touch the Version 2.0 patches, Version 1.0 patches, or the GT\_Analog Project you wish to load.

**Note:** The option of loading these different sets of patches is only available if you've updated to Version 2.0. (You can download the latest free V-Synth GT operating system software from [here](#).)

- 4 Touch **OK**.
- 5 When the V-Synth GT asks if you're sure you want to proceed, touch **OK**.



## V-Synth GT

### How Do I Find V-Synth GT Articles in the RolandUS.com Knowledge Base?

---

- 1 Point your browser to the V-Synth GT [Support area](#) on RolandUS.com.
- 2 Click “Knowledge Base.”  
If you’re not already logged into Roland Backstage, the Roland Backstage login appears.
- 3 If you’re:
  - *a Roland Backstage member*—enter your email address and password, and then click the Login button.
  - *not yet a Roland Backstage member*—click “Create New Profile” to create a free new user account. As a Roland Backstage member, you become part of the online Roland US.com community and gain access to helpful tools and services.
- 4 Once you’re logged in, click the large Knowledge Base button.
- 5 On the Knowledge Base screen, enter “V-Synth GT” in the Product field.
- 6 Click the Find button in the middle of the screen to browse the available V-Synth GT Knowledge Base articles.