

# MA-15DBK

## Digital Stereo Micro Monitor

EDIROL  
by Roland

### Now Available in Black

The MA-15D stereo reference monitors are ideal for computer-based recording artists seeking a high-quality, powerful set of reference speakers to use in a small space. The 15-watt-per-channel MA-15D's offer a wide-range spectrum and crystal-clear audio reproduction. Now available in an attractive black wooden cabinet!

- 3 independent source inputs: 1/8", RCA (L/R), and S/PDIF (optical & coaxial); 1/4" headphone port
- 24-bit/192kHz support
- Bass Enhancer; Subwoofer output port for bass boost



\*Actual product appearance may be subject to change.

- Front-controlled bass, treble, and 2 independent volume controls
- 100 mm (4") woofer + 50 mm (2") tweeter, 2 way bass-reflex enclosure; magnetically shielded

#### MA-15DBK Specifications

■ **Rated Power Output** 30 W (15 W + 15 W) ■ **Speaker Units** Woofer: 10 cm / 3-15/16" (Magnetically-Shielded), Tweeter: 5 cm / 2" (Magnetically-Shielded) ■ **Frequency Range** 70 Hz to 20 kHz ■ **Nominal Input Level** Line 1: -10 dBu, Line 2: -10 dBu ■ **Input Impedance** 20 kΩ ■ **Controls** <R Channel> BASS Control Knob, TREBLE Control Knob, VOLUME Knob x 2: VOLUME 1 (digital input + line 1), VOLUME 2 (RCA phono), POWER Switch, BASS ENHANCER Switch, Digital Input Select Switch ■ **Indicators** R Channel: Power Indicator ■ **Connectors** <R Channel> Front: PHONES Jack (stereo 1/4" phone type), Rear: LINE 1 Jacks (L, R) (stereo mini type), LINE 2 Jacks (L, R) (RCA phono type), L Channel Output Jack (RCA phono type), SUB-WOOFER Output Jack (RCA phono type), Digital Input Connector (Optical), Digital Input

Connector (Coaxial) <L Channel> Rear: L Channel Input Jack (RCA phono type) ■ **Digital Input Section** Sampling Rate: 32/44.1/48/96/192kHz, D/A Converter: 24 bits ■ **Enclosure** 2-way Bass-reflex type (Wooden Cabinet) ■ **Power Supply** AC 117 V, AC 220 V, AC 230 V or AC 240 V: 50/60 Hz ■ **Current Consumption** 45 W ■ **Dimensions** <R Channel> 158.5 (W) x 221.5 (D) x 250.0 (H) mm/ 6-1/4 (W) x 8-3/4 (D) x 9-7/8 (H) inches <L Channel> 158.5 (W) x 215.0 (D) x 250.0 (H) mm/ 6-1/4 (W) x 8-1/2 (D) x 9-7/8 (H) inches ■ **Weight** <R Channel> 5 kg / 11 lbs 1 oz <L Channel> 2.5 kg / 5 lbs 9 oz ■ **Accessories** Owner's Manual, Speaker Cable (RCA phono type), Power Cord, Rubber Foot x 4

\* 0 dBu= 0.775 Vrms

\* The specifications are subject to change without notice.

# MA-7ABK

## Stereo Micro Monitor

EDIROL  
by Roland

### Now Available in Black

The MA-7A Stereo Reference Speakers are the ideal solution for musicians and computer users who demand the best audio quality possible in a very confined space. The 7-watt-per-channel MA-7As are extraordinarily small reference speakers, but are capable of producing incredible sound. Now available in an attractive black wooden cabinet!

- 2 independent source inputs: 1/8" and RCA (L/R); 1/8" headphone port
- Front-accessible Volume & Tone controls



\*Actual product appearance may be subject to change.

- Bass Enhancer; Subwoofer output for bass boost
- 76mm (3") full-range speaker, bass-reflex enclosure
- Magnetically shielded

#### MA-7ABK Specifications

■ **Rated Power Output** 14 W (7 W + 7 W) ■ **Speaker Units** Woofer: 9 cm / 3-9/16" (Magnetically-Shielded) ■ **Frequency Range** 90 Hz to 20 kHz ■ **Nominal Input Level** Line 1: -10 dBu, Line 2: -10 dBu ■ **Input Impedance** 20 kΩ ■ **Controls** <R Channel> BASS Control Knob (BASS ENHANCER Switch), TREBLE Control Knob, VOLUME Knob, STANDBY Switch ■ **Indicators** <R Channel> STANDBY Indicator ■ **Connectors** <R Channel> Front: PHONES Jack (stereo 1/4" phone type), LINE Input Jack (stereo mini type), Rear: LINE 1 Input Jack (stereo mini type), LINE 2 Input Jacks (L, R) (RCA phono type), L Channel Output Jack (RCA phono type), SUB-WOOFER Output Jack (RCA phono type) <L Channel> Rear: L Channel Input Jack (RCA

phono type) ■ **Enclosure** Full-range Bass-reflex type (Wooden Cabinet) ■ **Power Supply** AC 117 V, AC 220 V, AC 230 V or AC 240 V: 50/60 Hz ■ **Current Consumption** 22 W ■ **Dimensions** <R Channel> 145.0 (W) x 194.2 (D) x 215.0 (H) mm/ 5-3/4 (W) x 7-11/16 (D) x 8-1/2 (H) inches <L Channel> 145.0 (W) x 187.6 (D) x 215.0 (H) mm/ 5-3/4 (W) x 7-7/16 (D) x 8-1/2 (H) inches ■ **Weight** <R Channel> 3.4 kg / 7 lbs 8 oz <L Channel> 1.8 kg / 4 lbs ■ **Accessories** Owner's Manual, Speaker Cable (RCA phono type), Power Cord, Rubber Foot x 4

\* 0 dBu= 0.775 Vrms

\* The specifications are subject to change without notice.