

Authentic Loop Station in a Stomp Box

No company creates Loop Stations like BOSS. Already in heavy demand around the world are the twin-size BOSS RC-20XL and the deluxe, extra-wide RC-50. Now comes an ultra-compact member of the RC family, the RC-2. Housed in a compact-pedal case, the RC-2 puts a surprising amount of features in a stompbox.



*Actual product appearance may be subject to change.

- Up to 16 minutes of record time
- Loop Quantize for perfect loop timing
- Realistic Guide-Tone drum patterns built in
- Easy, logical overdubbing and navigation
- Undo / Redo function
- 11 phrases can be stored and recalled
- AUX input to capture phrases from external audio device
- External pedal input (stop/tempo)

Record, Layer, Loop, & Store

The RC-2 can record and store up to 16 mono minutes of audio, either from your own instrument or other external input devices, such as MP3 players / recorders. Each of your layered loop creations can be stored to one of 11 internal patch preset locations.

Feature Rich

It records, layers, and loops, but the RC-2 also provides a wealth of other handy and powerful features, such as a jam-along Rhythm Guide, Auto Start, Tap Tempo, Loop Quantize, and Undo / Redo.

Friendly Operation

In traditional BOSS fashion, the RC-2 benefits from a clean and friendly user interface. As powerful as this little Loop Station is, it's a dream to operate. Thanks to its clearly labeled buttons and knobs, the RC-2 puts everything directly under your fingertips, with no hidden menus or commands to impede the creative process.

Pedalboard Ready

Thousands of guitarists rely on BOSS' ultra convenient BCB-series pedalboards for organizing their effects pedals. Due to its standard compact-pedal shape and size, the RC-2 fits perfectly alongside other BOSS pedals. Great for fast setup and convenient transportation.

Meet the Family

Thanks to the RC-2, there's now a BOSS Loop Station for every size and budget. With the super-deluxe RC-50 at the top of the line, and the twin-size RC-20XL in the middle of the range, the RC-2 represents the most compact and affordable Loop Station.



■ **Controls** Pedal switch, PHRASE LEVEL knob, GUIDE LEVEL knob, PHRASE SELECT knob, TAP TEMPO (ENTER / SELECT) button, MODE switch ■ **Indicators** CHECK indicator (Serves also as battery check indicator), LOOP / ONE SHOT indicator, REC / PLAY / DUB indicator, TAP TEMPO / SELECT / ENTER indicator ■ **Connectors** INPUT jack, OUTPUT jack, STOP / TEMPO jack, AUX IN jack, AC adaptor jack (DC 9 V) ■ **Nominal Input Level** -20 dBu ■ **Input Impedance** 1 M Ω ■ **Nominal Output Level** -20 dBu ■ **Output Impedance** 1 k Ω ■ **Recommended Load Impedance** 10 k Ω or greater ■ **Power Supply** DC 9 V: Dry battery / 9 V type (6F22 (carbon), 6LR61 (alkaline)), AC Adaptor (PSA-series: optional) ■ **Current Draw** 50

mA (DC 9 V), * Expected battery life under continuous use: Carbon: 2 hours, Alkaline: 6 hours. These figures will vary depending on the actual conditions of use. ■ **Dimensions** 70 (W) x 125 (D) x 55 (H) mm, 2-13/16 (W) x 4-15/16 (D) x 2-3/16 (H) inches ■ **Weight** 420 g / 15 oz (including battery) ■ **Accessories** Owner's Manual, Leaflet ("USING THE UNIT SAFELY," "IMPORTANT NOTES," and "Information"), Dry battery / 9 V type (6LR61) ■ **Option** AC Adaptor (PSA-series), Foot Switch FS-5U, FS-6

* 0 dBu= 0.775 Vrms

* The specifications are subject to change without notice.